


FM LOW PASS HARMONIC FILTERS



FEATURES


- High Rejection Through 5h Harmonic
- Low Insertion Loss and VSWR
- Constructed of Naval Brass and Heavy Wall Copper
- Many Power Ratings Available

5kW Low Pass Filter HF-158




Frequency Range	88—108 MHz
Power Rating	5 kW
VSWR	1.1:1
Impedance	50 Ω
Insertion Loss	0.1 dB
Rejection, 2nd through 5th Harmonic	>40 dB
Connectors	1-5/8" EIA
Length	71.0"
Diameter	2-1/8"

15kW Low Pass Filter HF-318-15



Frequency Range	88—108 MHz
Power Rating	15 kW
VSWR	1.1:1
Impedance	50 Ω
Insertion Loss	0.1 dB
Rejection, 2nd through 5th Harmonic	>40 dB
Connectors	1-5/8" EIA
Length	79.13"
Diameter	3-1/8"

25kW Low Pass Filter HF-318



Frequency Range	88—108 MHz
Power Rating	25 kW
VSWR	1.1:1
Impedance	50 Ω
Insertion Loss	0.1 dB
Rejection, 2nd through 5th Harmonic	>40 dB
Connectors	3-1/8" EIA
Length	96.0"
Diameter	4-1/16"